

Mini-TAC Pro



265 Lumens

- Momentary or constant-on, plus 3 user-selectable brightness settings plus strobe
- Aircraft-grade 6061-T6 aluminum housing
- Small light-weight design

The Nightstick MT-220 Mini-TAC Pro uses an LED and has a deep parabolic reflector creating a tight, long throw beam for distance illumination. With a waterproof design, this light is constructed from aircraft-grade 6061-T6 aluminum with a Type III hard anodized finish. The tail switch provides momentary or constant-on functionality, a set of user-selectable high, medium or low-brightness settings as well as a disorienting strobe. The light comes with a removable pocket clip and is powered by two AA batteries.



MT-220

MT 220



High-efficiency deep parabolic reflector

FEATURES

- LED technology – 50,000 + hours
- Momentary or constant-on flashlight plus 3 brightness levels & strobe
- Sharp focused flashlight beam
- Aircraft-grade 6061-T6 aluminum
- Type III hard anodized finish
- Non-slip grip
- Waterproof
- Impact & chemical resistant
- Meets the requirements of NFPA-1971-8.6 (2013)
- Powered by: 2 AA batteries
- Limited Lifetime Warranty*

MT-220 SPECIFICATIONS

FL1 STANDARD	HIGH	MEDIUM	LOW
	265 LUMENS	130 LUMENS	90 LUMENS
	2h 30min	8h	18h
	100m	73m	56m
	2486cd	1335cd	797cd



- Length: 6in,
head diameter: 0.9in,
handle diameter: 0.6in,
weight: 3.2oz



Handheld



High-efficiency deep parabolic reflector



Large textured tail-switch

INCLUDED

- Flashlight
- Removable pocket clip
- 2 AA batteries



Model	Description	UPC 0 17398
MT-220	Mini-TAC Pro flashlight with 2 AA battery, and removable pocket clip	80374 8

*Limited Lifetime Warranty • Product is warranted to be free from defects in workmanship and materials for the original purchaser's lifetime. The Limited Lifetime Warranty includes the LEDs, housing and lenses. Rechargeable batteries, chargers, switches, electronics and included accessories are warranted for a period of two (2) years with proof of purchase. Disposable, non-rechargeable batteries are excluded from this warranty. Normal wear and failures which are caused by accidents, misuse, abuse, faulty installation and lightning damage are also excluded.